

19" MODEL CGM-1901CW

Service Manual Supplement

REPLACEMENT PARTS LIST

MAIN BOARD			
Circuit No.	DESCRIPTION		
F801	FUSE, 250V 3A(SLOW-BLOW)	Q302	Transistor, KSC5088 & BU2508
U801	IC POWER, STK73410II	Q303,Q304	Transistor, MPSA92 & KSP92
D801	Diode Bridge, PBS408GU	Q305	Transistor, KSC945C
D803	Diode fast recovery, RG10 & RG2	Q306	Transistor, KSB601
D804	Diode fast recovery, RG10 & RG2	Q307	Transistor, KSA916 & KTA1023
D805	Diode fast recovery, 1N4935	Q308	Transistor, KSC2316 & KTC1027
D806	Diode fast recovery, 1N4937	Q309	Transistor, KSP42
T801	Power transformer, DST-1901C1	T301	Transformer H-Drive, DST 008A
U201	IC vertical output, DBL2054D	T302	Transformer Fly-Back, FNA-0012
D202	Diode rectifier, 1N4002	NECK BOARD	
Q201	Transistor, KSC3203	Circuit No.	DESCRIPTION
Q202	Transistor, KSA1271	U401	IC video pre-amp., LM1203N
D101-110	Diode switching, 1N4148	Q401-403	Transistor, KSC945C
U101	IC E-OR gate, GD4070	Q404-406	Transistor, KSC3503
Q101-103	Transistor, KSC945C	VR401	Semi-Variable Resistor, 100Ω
U301	IC horizontal sync., LA7851	VR402	Semi-Variable Resistor, 100Ω
U302	IC OP amp., LM358	VR403	Semi-Variable Resistor, 1kΩ
D301	Diode damper, RU4DS	VR404	Semi-Variable Resistor, 1KkΩ
D302	Diode fast recovery, FR154	VR405	Semi-Variable Resistor, 1kΩ
D303	Diode switching, 1N4148	CONTROL BOARD	
D304	Diode zener 1/4W 12V, 1N5242	Circuit No.	DESCRIPTION
D305	Diode fast recovery, 1N4937	VR1	Semi-Variable Resistor, 5kΩ
D306-309	Diode switching, 1N4148	VR2	Semi-Variable Resistor, 5kΩ
D310	Diode fast recovery, 1N4937	VR3	Semi-Variable Resistor, 100kΩ
D311-313	Diode fast recovery, 1N4935	VR4	Semi-Variable Resistor, 10kΩ
D314	Diode zener 1/4W 27V, 1N5250	VR5	Semi-Variable Resistor, 20kΩ
Q301	Transistor, KSC2316	VR6	Semi-Variable Resistor, 100kΩ

